

## Olex M1 BIOS-innstillinger

Trykk DEL i oppstarten for å komme til "BIOS setup", og gjør følgende endringer:

- Advanced Bios features -> Boot Sequence
  - First Boot Device [USB-CDROM] eller [CDROM]
  - Second Boot Device [Hard-Disk]
- Advanced Chipset Features -> VGA Setup
  - Display Type [CRT + DVI]
  - Panel Type [1280 X 1024 36Bit]
- Integrated Peripherals -> Onboard Device
  - USB Keyboard Support [Enabled]
- Integrated Peripherals -> Super IO Device
  - PWRON After PWR-Fail [Former Sts]
  - Serial Port 3 Use IRQ [IRQ 10]
  - Serial Port 4 Use IRQ [IRQ 11]

Trykk **F10** og "y" for å lagre endringene og starte maskinen.

## Olex M2 BIOS-innstillinger

Trykk DEL i oppstarten for å komme til "BIOS setup", og gjør følgende endringer:

- Chipset
  - ▷ South Bridge  
Restore AC Power Loss = [Last state]
- Boot
  - ▷ Boot Option #1 = [The DVD reader]

Valg av USB-CD/DVD-leser som første boot-medium må gjøres hver gang man skal "boote" fra DVD og leseren må være tilkoblet for at den skal være å finne i BIOS. Trykk **F4** og <ENTER> for å lagre endringene og starte maskinen.

## Olex M3 BIOS-innstillinger

Trykk DEL i oppstarten for å komme til "BIOS setup", og gjør følgende endringer:

- Advanced
  - ▷ Super I/O Configuration  
Restore AC Power Loss = [Last state]
- Boot
  - ▷ Boot Option #1 = [UEFI: KingstonDataTravele...]
  - ▷ Hard Drive BBS Priorities ▷ Boot Option #1 = [KingstonDataTravele...]

Trykk **F4** og <ENTER> for å lagre endringene og fortsette oppstarten.